TOSHIBA Transistor Silicon NPN Epitaxial Type (PCT Process)

RN1207,RN1208,RN1209

Switching, Inverter Circuit, Interface Circuit
And Driver Circuit Applications

- With built-in bias resistors.
- Simplify circuit design
- Reduce a quantity of parts and manufacturing process
- Complementary to RN2207~2209

Unit: mm



JEDEC	—
EIAJ	—
TOSHIBA	2-4E1A

Weight: 0.13g

Equivalent Circuit and Bias Resistor Values



Type No.	R1 (kΩ)	R2 (kΩ)
RN2207	10	47
RN2208	22	47
RN2208	47	22

Maximum Ratings (Ta = 25°C)

Characteristic		Symbol	Rating	Unit
Collector-base voltage		V_{CBO}	50	V
Collector-emitter voltage		V_{CEO}	50	V
Emitter-base voltage	RN1207	V_{EBO}	6	V
	RN1208		7	
	RN1209		15	
Collector current		I_C	100	mA
Collector power dissipation		P_C	300	mW
Junction temperature		T_j	150	°C
Storage temperature range		T_{stg}	−55~150	°C

Electrical Characteristics (Ta = 25°C)

Characteristic		Symbol	Test Circuit	Test Condition	Min	Typ.	Max	Unit
Collector cut-off current		I_{CBO}	—	V_{CB} = 50V, I_E = 0	—	—	100	nA
		I_{CEO}	—	V_{CE} = 50V, I_B = 0	—	—	500	nA
Emitter cut-off current	RN1207	I_{EBO}	—	V_{EB} = 6V, I_C = 0	0.081	—	0.15	mA
	RN1208		—	V_{EB} = 7V, I_C = 0	0.078	—	0.145	
	RN1209		—	V_{EB} = 15V, I_C = 0	0.167	—	0.311	
DC current gain	RN1207	h_{FE}	—	V_{CE} = 5V, I_C = 10mA	80	—	—	—
	RN1208		—		80	—	—	
	RN1209		—		70	—	—	
Collector-emitter saturation voltage		$V_{CE\ (sat)}$	—	I_C = 5mA, I_B = 0.25mA	—	0.1	0.3	V
Input voltage (ON)	RN1207	$V_{I\ (ON)}$	—	V_{CE} = 0.2V, I_C = 5mA	0.7	—	1.8	V
	RN1208		—		1.0	—	2.6	
	RN1209		—		2.2	—	5.8	
Input voltage (OFF)	RN1207	$V_{I\ (OFF)}$	—	V_{CE} = 5V, I_C = 0.1mA	0.5	—	1.0	V
	RN1208		—		0.6	—	1.16	
	RN1209		—		1.5	—	2.6	
Translation frequency		f_T	—	V_{CE} = 10V, I_C = 5mA	—	250	—	MHz
Collector output capacitance		C_{ob}	—	V_{CB} = 10V, I_E = 0, f = 1MHz	—	3	6	pF
Input resistor	RN1207	R1	—	—	7	10	13	kΩ
	RN1208		—		15.4	22	28.6	
	RN1209		—		32.9	47	61.1	
Resistor Ratio	RN1207	R1/R2	—	—	0.191	0.213	0.232	—
	RN1208		—		0.421	0.468	0.515	
	RN1209		—		1.92	2.14	2.35	

RN1207 I_C – $V_{I(ON)}$



RN1207 I_C – $V_{I(OFF)}$



RN1208 I_C – $V_{I(ON)}$



RN1208 I_C – $V_{I(OFF)}$



RN1209 I_C – $V_{I(ON)}$



RN1209 I_C – $V_{I(OFF)}$



RN1207 h_{FE} – I_C



RN1208 h_{FE} – I_C



RN1209 h_{FE} – I_C



RESTRICTIONS ON PRODUCT USE

000707EAA

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
  In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the “Handling Guide for Semiconductor Devices,” or “TOSHIBA Semiconductor Reliability Handbook” etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury (“Unintended Usage”). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer’s own risk.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.